



# SHIFNOID NCRPM4000 ADJ-A-CHIP

## RPM = OHMS RESISTANCE CHART

| 3000 = 190 | 4150 = 282 | 5300 = 385 | 6450 = 502 | 7600 = 636 | 8750 = 780 |
|------------|------------|------------|------------|------------|------------|
| 3050 = 194 | 4200 = 286 | 5350 = 390 | 6500 = 508 | 7650 = 642 | 8800 = 786 |
| 3100 = 198 | 4250 = 290 | 5400 = 395 | 6550 = 514 | 7700 = 649 | 8850 = 792 |
| 3150 = 202 | 4300 = 295 | 5450 = 400 | 6600 = 519 | 7750 = 655 | 8900 = 798 |
| 3200 = 205 | 4350 = 299 | 5500 = 404 | 6650 = 525 | 7800 = 661 | 8950 = 805 |
| 3250 = 209 | 4400 = 304 | 5550 = 409 | 6700 = 532 | 7850 = 668 | 9000 = 811 |
| 3300 = 213 | 4450 = 308 | 5600 = 413 | 6750 = 537 | 7900 = 675 | 9050 = 817 |
| 3350 = 217 | 4500 = 312 | 5650 = 418 | 6800 = 542 | 7950 = 681 | 9100 = 823 |
| 3400 = 220 | 4550 = 316 | 5700 = 423 | 6850 = 547 | 8000 = 687 | 9150 = 830 |
| 3450 = 224 | 4600 = 320 | 5750 = 428 | 6900 = 553 | 8050 = 694 | 9200 = 837 |
| 3500 = 228 | 4650 = 325 | 5800 = 433 | 6950 = 559 | 8100 = 700 | 9250 = 844 |
| 3550 = 232 | 4700 = 330 | 5850 = 438 | 7000 = 564 | 8150 = 706 | 9300 = 851 |
| 3600 = 236 | 4750 = 334 | 5900 = 444 | 7050 = 571 | 8200 = 712 | 9350 = 858 |
| 3650 = 240 | 4800 = 338 | 5950 = 449 | 7100 = 577 | 8250 = 718 | 9400 = 865 |
| 3700 = 244 | 4850 = 343 | 6000 = 454 | 7150 = 582 | 8300 = 724 | 9450 = 872 |
| 3750 = 248 | 4900 = 347 | 6050 = 459 | 7200 = 587 | 8350 = 730 | 9500 = 879 |
| 3800 = 252 | 4950 = 352 | 6100 = 464 | 7250 = 593 | 8400 = 736 | 9550 = 886 |
| 3850 = 256 | 5000 = 357 | 6150 = 469 | 7300 = 599 | 8450 = 742 | 9600 = 893 |
| 3900 = 260 | 5050 = 361 | 6200 = 474 | 7350 = 605 | 8500 = 749 | 9650 = 900 |
| 3950 = 264 | 5100 = 365 | 6250 = 480 | 7400 = 611 | 8550 = 755 | 9700 = 907 |
| 4000 = 269 | 5150 = 370 | 6300 = 485 | 7450 = 617 | 8600 = 761 | 9750 = 914 |
| 4050 = 273 | 5200 = 375 | 6350 = 491 | 7500 = 623 | 8650 = 767 | 9800 = 921 |
| 4100 = 278 | 5250 = 380 | 6400 = 496 | 7550 = 630 | 8700 = 773 | 9850 = 928 |

SHIFNOID LTD.

*NCRPM4000*

*ADJ – A – CHIP*

The ADJ-A-CHIP is preset during manufacturing at approximately 6000 RPM. To lower the RPM level, turn the screw on the top of the ADJ-A-CHIP counter clockwise  $\frac{1}{4}$  turn for a 100 RPM drop. To raise the RPM level, turn the screw clockwise  $\frac{1}{4}$  turn for a 100 RPM gain. If you do not have a starting place or for more accuracy, refer to the OHMS resistance = RPM chart.