

HR and HM

1/4" x various length and SFE in-line fuse holder



Product features

- Bayonet type knob
- Maximum current rating 20 amps; voltage rating 32 volts AC
- Holders available as complete assembly consisting of in-line holder with 8" or 14" of #14 insulated wire and installed fuses
- Replacement springs – BK/1A1853
- Replacement contacts – 9838 for #18 - #22 wire, 9841 for #12 - #16 wire

Environmental data:

Temperature Rating (RTI): +140 °C

Agency information:

No agency listing

Part Number	Amps	Volts AC	Includes Fuse	Wire
HRJ*	20	32	SFE-20	19" of #14
HRI			SFE-14	
HRH			SFE-9	
HRE			SFE-7½	
HRG			SFE-6	
HRF			SFE-4	8" of #14
HMJ**			SFE-20	
HMI			SFE-14	
HMH			SFE-9	
HME			SFE-7½	
HMG	SFE-6			
HMF	SFE-4			

*Also available as in-line fuseholder only with lead wire contacts, HRJ-Less-Fuse.

**Also available as in-line fuseholder only with lead wire contacts, HMJ-Less-Fuse.

HDJ-A – For ¼" x 1¼" fuse, no wire or fuse included, accepts #18 - #20 wire.

HDJ-B – For ¼" x 1¼" fuse, no wire or fuse included, accepts #12 - #16 wire.

HDI-A – For ¼" x 7/8" fuse, no wire or fuse included, accepts #18 - #20 wire.

HDI-B – For ¼" x 7/8" fuse, no wire or fuse included, accepts #12 - #16 wire.

HAF-A – For ¼" x 5/8" fuse, no wire or fuse included, accepts #18 - #20 wire.

Dimensions: in (mm): All dimensions ±0.015"

