

| ALKALINE | Duracell | IEC | Energizer/Ucar | Varta | Kodak | Panasonic | Rayovac | Philips | RECHARGEABLES | Duracell | IEC | Germany | Italy | Others |
|----------|-------------|-------|----------------|-----------|-------|-----------|---------|---------|---------------|----------|------|---------|--------------|-------------------------|
| | AA MN1500 | LR6 | E91 | 4206/4006 | KAA | AM3 | 815 | LR6 | | HR6 | HR6 | MICRO | STILO | 4006, E91, KAA, R6, UM3 |
| | AAA MN2400 | LR03 | E92 | 4203/4003 | K3A | AM4 | 824 | LR03 | | HR03 | HR03 | MIGNON | MINI-STILO | 4003, E92, K3A, R0, UM4 |
| | C MN1400 | LR14 | E93 | 4014 | KC | AM2 | 814 | LR14 | | HR14 | HR14 | BABY | MEZZA-TORCIA | 4014, E93, KC, R14, UM2 |
| | D MN1300 | LR20 | E95 | 4020 | KD | AM1 | 813 | LR20 | | HR20 | HR20 | MONO | TORCIA | 4020, E95, KD, R20, UM1 |
| | 9V MN1604 | 6LR61 | 522 | 4022 | K9V | 6AM6 | A1604 | 6LR61 | | HR9V | HR9V | E-BLOCK | TRANSISTOR | 422, 4022, 6F22, K9V |
| | 4.5V MN1203 | 3LR12 | - | - | - | - | - | - | | | | | | |

| PHOTO | Duracell | IEC | Energizer/Ucar | Varta | Kodak | Panasonic | Rayovac/Vidor | Seiko | Sony | Philips | Renata | Others |
|-------|----------|----------|------------------------------|----------------|-------------------|-----------|------------------|-------|--------|---------|-----------------|-----------------------------------|
| | 123 | CR17345 | EL123AP EL123A EL123 | CR123A V123 | K123LA KL123LA | CR123A | CR123R | - | CR123 | - | - | DL123A |
| | 223 | CR-P2 | EL223AP EL223 | VL223 | K223L K223LA | CRP2P | PC223 | - | CR2PS | - | - | DL223, CR-P2S, CR-P2 |
| | 245 | 2CR5 | 2CR5 EL2CR5 | 2CR5 | KL2CR5 | 2CR5M | 2CR5R | - | 2CR5 | - | - | DL245 |
| | CR2 | CR17355 | CR2 ELCR2 | CR2 | KCR2 | CR2 | - | - | CR2B | - | - | DLCR2, RLCR2 |
| | CR-V3 | - | CR-V3 | - | CR-V3 | CR-V3 | - | - | - | - | - | CR-V3, ELCRV3 |
| | 625A | LR9 | EPX625G V625U (V625PX) | 625A | KA625 (KX625) | LR9/H-D | R625 (RPX625) | 625A | - | - | - | EPX625, EPX625A, KX625, MR9 |
| | 28L | 2CR11108 | L544 E23A-A23 | V28PXL | K28L | - | - | - | - | - | - | 4G13, 7H34, PS28L, 2CR1/3N |
| 1/3N | CR11108 | 2L76 | CR1/3N | K58L | - | - | - | CR1/3 | CR1/3N | - | DL1/3N, VCR1/3N | |

| ELECTRONIC | Duracell | IEC | Energizer/Ucar | Varta | Kodak | Panasonic | Rayovac/Vidor | Seiko | Sony | Philips | Renata | Others |
|------------|--------------------|--------|----------------|---------------|--------------|------------------|--------------------|----------------|--------|---------|-------------|------------------------------------|
| | 1220 | CR1220 | ECR1220 | CR1220 | - | CR1220 | - | - | CR1220 | - | - | DL1220 |
| | 1616 | CR1616 | ECR1616 | CR1616 | - | CR1616 BR1616 | CR1616 | - | CR1616 | - | - | DL1616 |
| | 1620 | CR1620 | ECR1620 | CR1620 | - | CR1620 | 1620 | - | - | - | - | DL1620 |
| | 2016 | CR2016 | ECR2016 | CR2016 | KCR2016 | CR2016 BR2016 | KECR2016-1 | CR2016 | CR2016 | CR2016 | - | DL2016, LF-1/4V, KL2016, BR2016 |
| | 2025 | CR2025 | ECR2025 | CR2025 | KCR2025 | CR2025 | KECR2025-1 | CR2025 | CR2025 | CR2025 | - | DL2025, KL2025 |
| | 2032 | CR2032 | ECR2032 | CR2032 | KCR2032 | CR2032 BR2032 | KECR2032-1 | CR2032 | CR2032 | CR2032 | - | DL2032, LF-1/2V, KL2032 |
| | 2430 | CR2430 | ECR2430 | CR2430 | K2430L | CR2430 | CR2430 | - | - | CR2430 | - | DL2430, LF-1/2W |
| | 2450 | CR2450 | ECR2450 | CR2450 | - | CR2450 | CR2450 | - | - | - | - | DL2450, CR2450 |
| | 357/303 R357/77 | SR44 | 357 303 | V357 V76PX | KS35 KS76 | SR44W | 357 RS76 | SR44W SB-B9 | SR44W | 357 | 357 | D357, SR44W, SB-B9, 10L14, J |
| | LR43 | LR43 | 186 | V12GA | KA43 | LR43 | RW84 | LR43 | LR43 | 186 | - | - |
| | LR44 | LR44 | A76 | V13GA | KA76 | LR44 | RW82 303/357-1W | LR44 | LR44 | A76 | - | 904, G13, LR1154, PX76A |
| | LR54 GP89A | LR54 | 189 | V10GA | KA54 | LR54 | RW89 | - | LR1130 | - | - | LR1130, AG10 |
| AAAA | - | - | - | - | - | - | - | - | - | - | MN2500, E96 | |

| WATCH | Duracell | IEC | Energizer/Ucar | Varta | Kodak | Panasonic | Rayovac/Vidor | Seiko | Citizen | Philips | Renata | Others |
|-------|----------|------|----------------|--------------|----------------|------------------------------------|---------------------------------|---|------------------|---------|--------|--|
| | 362/361 | SR58 | 362 | V362 | KS362 | SR7215W | 362 RW310 | TR7215W SB-AK | 280-29 | 362 | 362 | D362, R362/12 |
| | 364 | SR60 | 364 | V364 | KS364 | SR6215W | 364 RW320 354-1W | TR6215W | 280-34 SB-AG | 364 | 364 | D364, R364/31 |
| | 371/370 | SR69 | 371 | V371 | KS371 | SR9205W | 371 RW415 RW315 | SR9205W SB-AN TR9205W SB-BN | 280-31 | - | 371 | D371, R371, R370 |
| | 377 | SR66 | 377 | V377 | KS377 | SR6265W | 377 RW329 376/377-1W | SR6265W SB-AW | 280-39 | 377 | 377 | D377, R377/37, BA |
| | 386/301 | SR43 | 386 | V386 | KS386 | SR43W SR435W | 386 RW44 | SR43W SB-B8 | 280-11 280-41 | - | 386 | D386, R386/6, H |
| | 389/390 | SR54 | 389 390 | V389 V390 | KS389 KS390 | SR1130W SR11305W | 389 RW49 390 RW39 | SR1130W SB-BU SR11305W SB-AU | 280-15 280-24 | 389 | 389 | D389, D390, R389/17, M, R390/11, 10L122 |
| | 391/381 | SR55 | 391 | V391 | K391 RW40 | SR1120W SB-B5 | 391 | TR1120W | 280-30 | 391 | 391 | D391, R391/23, L |
| | 392/384 | SR41 | 392 384 | V392 V384 | K392 K384 | SR41W SR415W | 392, RW47 384, RW37 392-1 | SR41W SB-B1 TR415W SB-A1 | 280-13 280-18 | 392 | 392 | D392, D384, R392/2, K, R384/10 |
| | 394 | SR45 | 394 | V394 | KS394 | SR365W SR9365W | 394 RW33 | SR9365W SB-A4 | 17 | - | 394 | D394, R394/15 |
| | 399/395 | SR57 | 399 395 | V399 V395 | KS399 KS385 | SR9275W SR927(926)5W SR9327W | 399, RW413 395, RW313 | TR927(926)W SB-BP TR927(9265W) SB-AP | 280-44 280-48 | - | 399 | D399, D395, R399/35, W, R395/25 |

| SECURITY | Duracell | IEC | Energizer/Ucar | Varta | Kodak | Panasonic | Rayovac/Vidor | Toshiba | Sony | Philips | Others |
|----------|----------|--------|----------------|-------|-----------|------------------|---------------|---------|-------|---------|---|
| | N | LR1 | E90 | 4001 | KN | AM5 | 810-2 | LR1G | LR15G | LR1 | MN9100, 114, 810, 910A, 5500, AM5, E90, LR1, N, R15 |
| | J | 4LR61 | 539 | 4018 | KJ | 4LR61 | RJ-1 | 4LR61 | - | 539 | 867, 1412P, J, V76PX, 7K67 |
| | MN21 | 8LR932 | A23 | V23GA | K23, K23A | LRV08PA LRV08 | R23A | - | - | - | 3LR50, A23, E23A, GP23A |
| MN27 | MN27 | - | - | - | - | - | - | - | - | - | |