

# Installation and Operation Instructions ED3794 FLEXIBLE DIRECTIONAL



#### WARNING!

Failure to install or use this product according to manufacturer's recommendations may result in property damage, serious injury, and/or death



Do not install and/or operate this safety product unless you have read and understood the safety information contained in this manual.

- Proper installation combined with operator training in the use, care, and maintenance of emergency warning devices are essential to ensure the
- safety of emergency personnel and the public.
  2. Emergency warning devices often require high electrical voltages and/or currents. Exercise caution when working with live electrical connections.
- This product must be properly grounded. Inadequate grounding and/or shorting of electrical connections can cause high current arcing, which
  can cause personal injury and/or severe vehicle damage, including fire.
- 4. Proper placement and installation is vital to the performance of this warning device. Install this product so that output performance of the system is maximized and the controls are placed within convenient reach of the operator so that they can operate the system without losing eye contact with the roadway.
- 5. Do not install this product or route any wires in the deployment area of an air bag. Equipment mounted or located in an air bag deployment area may reduce the effectiveness of the air bag or become a projectile that could cause serious personal injury or death. Refer to the vehicle owner's manual for the air bag deployment area. It is the responsibility of the user/operator to determine a suitable mounting location ensuring the safety of all passengers inside the vehicle particularly avoiding areas of potential head impact.
- It is the responsibility of the vehicle operator to ensure daily that all features of this product work correctly. In use, the vehicle operator should
  ensure the projection of the warning signal is not blocked by vehicle components (i.e., open trunks or compartment doors), people, vehicles or
  other obstructions.
- 7. The use of this or any other warning device does not ensure all drivers can or will observe or react to an emergency warning signal. Never take the right-of-way for granted. It is the vehicle operator's responsibility to be sure they can proceed safely before entering an intersection, drive against traffic, respond at a high rate of speed, or walk on or around traffic lanes.
- 8. This equipment is intended for use by authorized personnel only. The user is responsible for understanding and obeying all laws regarding emergency warning devices. Therefore, the user should check all applicable city, state, and federal laws and regulations. The manufacturer assumes no liability for any loss resulting from the use of this warning device.

#### CONTENTS:

1	Light Head
2	Screws
1	Installation Guide
1	Mounting Gasket
1	Bezel
1	Alcohol Wipe

#### SPECIFICATIONS:

Input Voltage	12-24VDC
Current	0.8A Max @ 12VDC 0.5A Max @ 24VDC
Physical H x W x L	3.9 in x 0.9 in x 0.4 in 9.9 cm x 2.3 cm x 1 cm
Ship Weight	0.1 lb (0.05 Kg)


Important! This unit is a safety device and it must be connected to its own separate, fused power point to assure its continued operation should any other electrical accessory fail.

Caution: When drilling into any vehicle surface, make sure the area is free from any electrical wires, fuel lines, vehicle upholstery, etc. that could be damaged.

#### Caution:

- light cannot be twisted or pulled
- do not bend in the lens direction
- Mounts to a surface curvature with a minimum radius of 3 inches.

Maximum flex is 120 degrees






Can not pull the wire because the PCB and components will be damaged.



No Twisting

The product can't be twisted because the PCB and components will be damaged.

### Mounting:



#### Mounting on a curved surface:

- Mark hole location using gasket as a template and drill hole for wire exit using 11/32 in. drill bit.
- 2. Wipe surface clean with alcohol wipe. Wait until dry.
- Mount light using VHB adhesive. Peel adhesive backing and apply pressure to adhere to surface for 20 seconds. It is recommended to allow 24 hours for adhesive to fully adhere before powering on light.
- \* Do not use hardware, gasket or bezel when mounting on curved surface.
- \* Max surface curvature 120°.

#### Mounting on flat surface:

- Mark wire and screw locations using gasket as a template. Drill wire exit hole using 11/32 in. drill bit. Pre-drill screw holes using 3/64 in. drill bit.
- Peel VHB backing and apply light to surface, aligning screw holes and wire exit. Apply pressure for 20 seconds. Insert screws through bezel to finish mounting lighthead. It is recommended to allow 24 hours for adhesive to fully adhere before powering on light.

\*For extra adhesion, use 3M Tape Primer. For product & application information, go to: https://multimedia.3m.com/mws/media/659520/3mtm-tape-primer-94.pdf

#### Wire:

RED: Positive, Colors 1 & 3 (need to add 5A fuse)
WHITE: Positive, Colors 2 & 4 (need to add 5A fuse)
RED & WHITE: Positive (Colors 1 & 3) & (Colors 2 & 4)
BLACK: Negative
BLUE: Pattern select to negative
YELLOW: Synchronized Function

# (Up to 8 units can be Synchronized) Operation Environment:

Ambient Temperature: -30 to 50°C (-22° F to 122°F

## Phase Operation:

Phase 1 (Ph1) flashes simultaneously with Ph1 Phase 2 (Ph2) flashes simultaneously with Ph2 Ph1 alternates with Ph2

(Up to 8 units can be Synchronized)

# Apply BLUE TO BLACK wire:

-Less than 1 sec. for next pattern -Between 1-3 sec for previous pattern -Between 3-5 sec. for factory default -More than 5 sec. for last pattern

12	11	10	9	œ	7								7					7						7						7							6									5								4								w								2								_					Pattern	1
à	ĸ			99	is is	: 33					32	31	30	23	28					27	26	25	24	23				***	3 12	20	19	18				***	17	16	16 14	13					12	= =	10	000					7	6	5	a u					2	1-Default	LED Color 1 & Color 3 Red line	=																				
36				0.00	35	33	32	31					30	29	28	27	26					25	24	23	22	21				20	19	- 81	17	16				61	16	13	12	11					10	0 00	7	6					35	a. u	2 63	1-Default					LED Color 2 & Color 4 White line																					
8 8	68	\$ 8	65	2:	8 8	61	60	59	58	57	%	35	54	S	52-Default	51	50	49	\$	47	46	45	4:	43	42	41	8	20	37	36	35	34	33	32	31	8 5	2 5	25	26	25	24	23	22	21	20	19	18	12 16	15	14	13	12	11	10	9		2 0		4	3	2	Red & White line	LED Color 2 & Color 4	Transcated a Color																				
Seatoly Burn-Color 2 & 4	Doubt Triple (Quad (Coort 1 Syllatronous color 3) Anamaety (Coort 2 Syllatronous Color 4)	4 Single 2 Triple (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)  1D color 1 Triple (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	2 Double 2 Quad (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	Mochilation (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	ECER65SAE Quad 60FPM (Color 1 Synchronous Color 2) Alternately (Color 2 Synchronous Color 4)  ECER65SAE Quad 60FPM (Color 1 Alternately Color 2) Alternately (Color 3 Alternately Color 4)	(Color 1 Synchronous Color 3) Alternately (Color 2	ECER6SSAE Quad 120FPM Ph2 Coker 2 Synchronous Color 4	ECER65SAE Quad 120FPM Ph1 Coker 2 Synchronous Color 4	ECER6SSAE Quad 120FPM Ph2 Color 1 Alternately Color 4	ECER65/SAE Quad 60FPM Ph 1 Color 1 Alternately Color 4	ECER65SAE Quad 120FPM Ph2 Coker 1 Synchronous Coker 3	ECER65SAE Quad 120FPM Ph1 Coke 1 Synchronous Color 3	SAE/T13 Quad 38FPM (Color 1 Alternately Color 2) Alternately (Cokr 3 Alternately Cokr 4)	SAE/T13 Quad 38 FPM Ph2 (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	SAET13 Quad 38FPM Ph I (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	SAE/T13 Quad 75 FPM Ph2 Color 2 Synchronous Co ker 4	SAET13 Quad 75FPM Ph I Color 2 Synchronous Color 4	SAE/T13 Quad 75FPM Ph2 Color 1 Alternately Color 4	SAE/T13 Quad 75FPM Ph I Color 1 Alternately Color 4	SAET13 Quad 75FPM Ph2 Color 1 Synchronous Color 3	SAE/T13 Quad 75FPM Ph 1 Color 1 Synchronous Color 3	SAE/T13 Triple 38FPM (Color 1 Alternately Color 2) Alternately (Cokr 3 Alternately Cokr 4)	SAE/T13 Triple 38FPM Ph2 (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	SAE/T13 Triple 38FPM Ph I (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	SAE/T13 Triple 7SFPM Ph2 Color 2 Synchronous Color 4	SAE/T13 Triple 75FPM Ph1 Color 2 Synchronous Color 4	2 Color 1 Alternately	SAE/T13 Teinle 25 EBM Db1 Color 1 Alternation Color 4	SAET13 Triple 75FPM Ph 1 Color 1 Synchronous Color 3	ECER65SAE Double 60FPM (Cohr 1 Alternately Cohr 2) Alternately (Color 3 Alternately Color 4)	ECER65/SAE Double 60FPM Ph2 (Co.ker 1 Synchronous Color 3) Alternately (Co.ker 2 Synchronous Color 4)	ECER65/SAE Double 60FPM Ph1 (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	ECER65SAE Double 120FPM Ph2 Color 2 Synchronous Color 4	ECER6SSAE Double 120FPM Ph1 Color 2 Synchronous Color 4	ECER6SSAE Double 120FPM Ph2 Color 1 A hornately Color 4	ECER6SSAE Dauble 120FPM Ph 1 Color 1 A lternately Color 4	ECEPASSAE Double 120 FM Fit Color 1 Synchronous Color 3		SAE/T13 Double 38FPM Ph2 (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	Synchronous Color 3) Alternately (Color 2 Synchronous	SAE/T13 Double 75FPM Ph2 Color 2 Synchronous Color 4	SAE/T13 Double 75FPM Ph1 Coker 2 Synchronous Color 4	SAE/T13 Double 75FPM Ph2 Color 1 Alternately Color 4	SAE/T13 Double 7 SFPM Ph1 Color 1 Alternately Color 4	SAE/TI3 Double 75FPM Ph2 Color 1 Synchronous Color 3	SAE/T13 Dauble 7 SEPM Ph1 Cabr 1 Swedronous Cohr 3	Single 187 FPM FPM (Color 1 Synchronous Coxor 3) Alternately (Color 2 Synchronous Coxor 4)  Single 187 FPM FPM (Color 1 Alternately Color 2) Alternately (Color 2 Synchronous Coxor 4)	Single 187 FPM FPM (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	Single 375FPMFPM Ph2 Color 2 Synchronous Color 4	Single 375FPMFPM Ph1 Co.kr 2 Synchronous Color 4	l Alternately Co	Single 375FPMFPM Ph1 Co ker 1 Alternately Color 4	Single 375FPMFPM Ph2 Color 1 Synchronous Color 3	Synchronou	SAE/T13 Single 38FPM (Color 1 Alternately Color 2) Alternately (Color 3 Alternately Color 4)	SAE/T13 Single 38FPM Ph/YColor 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)  SAE/T13 Single 38FPM Ph/YColor 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	SAETT13 Single 75FPM Ph2 Color 2 Synchronous Color 3 A Francisch (Color 2 Single concern Color 4)	Synchronous	SAET13 Single 75FPM Ph2 Coke 1 Alternately Coke 4	SAE/T13 Single 75FPM Ph1 Color 1 Alternately Color 4	SAE/T13 SAE/T13 Single 75FPM Ph2 Color 1 Synchronous Color 3	SAE/T13 SAE/T13 Single 75FPM Ph1 Color 1 Synchron	PATTERNS	ED3794 DUAL COLOR FLASH PATTERN CHART																				
	Т	N/A	H		, .T.	Т		l.		П		l.		m	Т	L	L	Γ	Þ			Н	m		[		× آ.		. [ .		¬	L	[	[	I	Т	. I.		π.	Т		L	Г	<b>&gt;</b>	I		. I.	Т		L		,	I		Т	,, , [.		I.	,	П			Mark S	N CHA																				
no v	2 2	8 8	no >	no 7	y S	yes	_	yes Cla				yes Cla	H	yes >	yes	yes Ck	yes Cl	H	yes >	Н	Н	H		4	_	_	yes >	_		yes	yes >	yes >	-	^		ves o	+	+	yes	t	H	┝		/cs	yes Ch	ves Class I	yes yes	+	-	yes >	/cs	/cs	yes >	œ i	à à	yo yo	+	+	Н	yes	_	ves Cl	SYNC	RT																				
N/C	, i	NO.	1/C	Č Č	ñ ĉ	i C	Class 1 Cla	Class 1 Cla	N/C N	Н	Class 1 Cla	Class 1 Cla	N/C N	I/C	N/C	Class 1 Cla	Class 1 Cla	H	I/C		Class 1 Cla	N/C N	N/C N	+		Class I Cla	č	۲.	Three 1 Cla	VC >	I/C	1/C N	1	llass 1 Cla		N/C		+	i c	N/C	-	H	N/C N	1/C N	-	c	N/C	t	N/C N		1/C N	1/C N	1/C	Č	č č	200	Class I Cla	Ė	H	Н	$^{+}$	Class I Cla																						
N/C		n c	N/C	C	Z C	VC .	F	lass 1 Ck			Class 1 Ch	Class 1 Ck	N/C N	VC P	N/C	Class 1 Ch	Class 1 Ck	-	N/C >	Н	Class 1 Ck	Н		_	-	_	NC S	NIC C	_	N/C	N/C	VC N	_	_		NO.	+	+	+	NC	_	+	N/C >	N/C N	Class 1 Ch	-		ł	NC Z	-	N/C N	VC N	N/C N	C Z	+	NO P	Class I Ca	╀		Н	Class I Ch	ISS C	SAE J 595																					
N/C N	N N	N N	N/C N	V.C		V/C	Class 1 Clas	Class 1 Clas			Class 1 Clas	Class 1 Clas	N/C N	I/C	N/C	Class 1 Cla	Class 1 Clas	╁	I/C N	Н	Class 1 Clas	N/C N	N/C N	$\dashv$		_	N/C N/C	NIC NI	+	H	H	I/C N	-	-	+	N/C	Ŧ	+	N/C	N/C	_	+	N/C N	I/C N	_	- C	N N	t	N/C N	H	I/C N	I/C N	I/C N	NC N	+	N/C	Class I Class I	+	H	V/C N/C	-	Class   Class																						
N/C N/C	NIC NIC		N/C N/C	1	NO NO	i C	Class 2 N	Class 2 N/C			Class 2 N/C	Class 2 N/C	N/C N/C	N/C	N/C	Class 2 N/C	Class 2 N/C	H	N/C N/C	Class 2 N/C	Class 2 N	N/C N/C	N/C N/C	N/C N	Class 2 N/C	2	/C	NIC NI	T	N/C N/C	N/C	/C N	Class 1 N/C	SS I		Ť	Class I NO	$^{+}$	+	N/C N/C	h	H	N/C N/C	/C N/C	+	+	+	NC NC		H	N/C N/C	V/C N	N/C N/C	+	+	N N	_	ss 1 Class B				_		-																				
C C	N N	O C	C N/C	C C	o o	C N	C N/	C N/	C N/	C N/	C N/	C N/	C N/C	C N/	C N	C N	C N	C N/	C N/	C N/	C N/	C N/	C N/	C N/	C N/	C N	C C	N C	N/C	C N	C N/	C N/	C N/	C N/	C N/	O O	N N	C C	S C	C	C N/	C N/	C N/	C N/	C N/	C C	S C	O C	C N/	C N/	C N/	C N/	C N/	C N	O O	N/C N/C	S B Class	t	C N/	C N/	Class B Class	AMBI	CAT13																					
C N/C	N/C	C N/C	Н	C N/C	N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	_	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	O N/C	N/A	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	N/C	N N	NIV.	N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	N/C	N/C	C N/C	C N/C	C N/C	C N/C	C N/C	C N/C	NC.	N/C	N/C	α	В			₩ .	# #																						
N/C			П													Т						C N/C						_	N/C	-								+								_								_							B NC																							
N/C	+	+	Н	+	+	+	H	-	Н			-	H	H	H	H	H	H	-			Н		+	N/C		N/C	Ť	_	_	_			_																													ECE R65																					
N/C	+	+	H	+	+	+	H			Н			H	H	t	t	t	H		Н	Н	N/C	Н	-	N/C		N/C	$^{+}$		N/C			l Class l		N/C			Char		N/C	1				N/C				1												N/C		55																					