

# GWH348

## WIRING COLOR CODES

(3) RED -Only one is used ..... 12V IGNITION

**\*NOTE:** You should use a volt ohm meter and test to determine which of the 3 RED wires your vehicle uses for switched 12 volts prior to connecting your radio's accessory or IGN wire. After determining which wire is correct on your car, cap off the remaining red wires so they will not touch anything or each other.

YELLOW ..... 12V BATTERY/MEMORY

BLACK ..... GROUND

BLUE/WHITE ..... AMP TURN-ON

BLACK/WHITE ..... AMP GROUND

ORANGE ..... ILLUMINATION

ORANGE/WHITE ..... DIMMER

GREY ..... RIGHT FRONT POSITIVE (+)

GREY/BLACK ..... RIGHT FRONT NEGATIVE (-)

WHITE ..... LEFT FRONT POSITIVE (+)

WHITE/BLACK ..... LEFT FRONT NEGATIVE (-)

VIOLET ..... RIGHT REAR POSITIVE (+)

VIOLET/BLACK ..... RIGHT REAR NEGATIVE (-)

GREEN ..... LEFT REAR POSITIVE (+)

GREEN/BLACK ..... LEFT REAR NEGATIVE (-)