



WIRE IDENTIFICATION

GREEN RIGHT TURN

YELLOW LEFT TURN

BROWN TAIL / PARK

WHITE ATTACH TO GROUND

1. Locate lighting system wires in trunk / rear of vehicle for driver and passenger side lighting functions.
2. Use the circuit tester provided to identify individual wires by function (right turn, left turn, tail). To use the circuit tester, attach the alligator clip to ground (frame, unpainted bolt, etc.). Turn on parking lights and pierce each wire with tester until it lights. Repeat this procedure for the remaining functions.
3. Use the splices provided to join the vehicle connector wires to the vehicle's corresponding function wires as determined in Step 2.
4. Attach the white wire to a clean surface on vehicle frame with screw provided. **NOTE:** Loose ground wires or grounds not attached directly to the vehicle frame may result in trailer light malfunction.
5. Secure any loose wiring to the vehicle with wire ties.
6. Apply grease to the wire harness trailer end to prevent corrosion.
7. Test all functions to assure proper installation with engine running.

NOTE: A heavy duty flasher may be needed to eliminate rapid flashing.

NOTE: Always unplug trailer connection before backing into water.