



IBBLF

Safety Flash Controller for Incandescent Third Brake Light

**NOTE: This controller is intended for the
Third Brake Light ONLY**



The IBBLF installs before the third brake light and flashes the light then goes solid when the brakes are applied. This provides a better visual warning of braking than the traditional solid brake light.

Instructions:

1. Locate the third brake light wiring. It may be accessible from inside the vehicle, if not then the wiring will be in the third brake light itself.
2. Once the wiring is located and verified with a DMM (Digital volt meter), cut the wire that goes to 12 volts when the brake is applied.
3. Attach the red wire of the IBBLF to the wire that goes to 12 volts when the brake is applied and the black wire to the other side of the cut wire.
4. Test safety flash controller by pressing on brake pedal. The third brake light will rapidly flash multiple times then remain lit until brake pedal is released.

NOTE: Make sure controller's wiring is not in an area that it will get damaged or pinched.

