

# SELF CANCELLING TURN SIGNAL UNIT

**AUTEC4=**

**Programmable Control Module**

The AUTEC4 is a driver-friendly, programmable device for self-cancelling turn signals. This unit allows you to limit the pulse length of your turn signals with ease. Ideal for push button turn signals, great for peace of mind.



## IMPORTANT INFORMATION!

- 1** You must use relays on ALL outputs except for Status LED output.
- 2** All outputs are negative trigger.

## Unit Operation

### Time Settings

1. Push button 1 for 5 seconds.
2. '1' will be displayed. Push button 1 again to confirm.
3. Press button 2 or 3 to adjust flasher pulse rate- how fast flashers flash.
4. Press button 1 to confirm.
5. Press button 2 or 3 until display shows number 2. Press button 1 to confirm.
6. Press button 2 or 3 to adjust output time (turn signal duration).
7. Press button 1 to confirm.
8. Press button 1 again to exit programming.

### Operation

1. Press left turn signal button, left turn signal will flash for output time duration. To exit, press right turn signal button.
2. Press right turn signal button, right turn signal will flash for output time duration. To exit press left turn signal button.

## Device Diagram

